Voltage Detectors Safety

Measuring instruments of low voltage



635 Tester BTL-600

Optical & Acoustic

Compact and convenient, highly accurate digital multimeter. Manual and automatic range adjustment. Pen type design that is easy to hold and use. Very safe, non-contact voltage detector function gives the user more confidence. Illuminated screen and torch allow use in all working environments, including in the dark. Diode test and continuity test functions.

Code	Ref.	Box
635300	Tester BTL-600	1

Technical information

PScreen: 2000 digits

Measuring range: Automatic and manual

■ Voltage range: DC 200 mV / 2 V / 20 V / 200 V / 600 V AC 200 mV / 2 V / 20 V / 200 V / 600 V

Current range: DC 20 mA / 200 mA
 AC 20 mA / 200 mA

■ Resistance range: $200 \Omega/2 k\Omega/200 k\Omega/2 M\Omega/20 M\Omega$

Other functions:

Diode test and Continuity test.

Data storage function

VCN mode: Non-contact voltage detection

Category: CAT III 600 V Certificates: CE, RoHS

Power supply: 2 x 1.5 V AAA batteries

Colour: Yellow

■ **Dimensions:** 248 × 42 × 34 mm

Weight: 110 g

Supplied with a nylon case for transport and storage.
According with standards EN61010-1, EN61010-2-033, EN61326 and IEC 62321.

5 sofamel