## Measuring instruments of low voltage

## 31009 BTL-600

True RMS tester - Optical & Acoustic

Compact and convenient, highly accurate digital multimeter. Manual and automatic range adjustment. Pen type design that is easy to hold and use. Very safe, non-contact voltage detector function gives the user more confidence. Illuminated screen and torch allow use in all working environments, including in the dark. Diode test and continuity test functions.

Code	Ref.	Box
635300	Tester BTL-600	1

Technical information

-	PScreen: Measuring range: Voltage range: Current range:	2000 digits Automatic and manual DC 200 mV / 2 V / 20 V / 200 V / 600 V AC 200 mV / 2 V / 20 V / 200 V / 600 V DC 20 mA / 200 mA
	B	AC 20 mA / 200 mA
	Resistance range:	$200\Omega/2\mathrm{k}\Omega/20\mathrm{k}\Omega/200\mathrm{k}\Omega/2\mathrm{M}\Omega/20\mathrm{M}\Omega$
	Other functions:	Diode test and Continuity test.
		Data storage function
	VCN mode:	Non-contact voltage detection
	Category:	CAT III 600 V
	Certificates:	CE, RoHS
	Power supply:	2 x 1.5 V AAA batteries
	Colour:	Yellow
	Dimensions:	248 × 42 × 34 mm
	Weight:	110 g
	o	

Supplied with a nylon case for transport and storage. According with standards EN61010-1, EN61010-2-033, EN61326 and IEC 62321.