



## 635 Digital multimeter DM-600


### Optical

Portable digital multimeter with backlit LCD display which allows values to be read even in dark locations.

The whole system is based on integrated circuits, equipped with overload protection. It can be used to measure AC and DC voltage, AC and DC current, resistance, capacitance, frequency, diodes and perform continuity and NCV (non-contact voltage detection) tests.

Code	Ref.	Box
635380	Digital multimeter DM-600	1

#### Technical information

- Automatic range
- Operating voltage: 600 VDC/AC
- Resistance ranges: 20 MΩ
- Diode test
- Capacitance: 2mF
- Current: 10A
- NCV function
- Frequency: 20kHz
- Display: 3 1/2 LCD
- Overload protection: PTC protection circuit is used to measure resistance and frequency
- Data storage
- Maximum measurement
- Out of range indicator: OL
- Low battery indicator: 
- Auto power off: 15 minutes. Press "HOLD/BL" to activate.
- Operating conditions: 0~40 °C (32~ 104 °F); <80% HR
- Storage conditions: -10~50 °C (14~122 °F); <70% HR
- Power supply: 1 No. 9 V battery (type 6F22, 1604A)
- Safety requirements: IEC61010-1 600 V CAT III
- Dimensions: 147:5x74x42.5 mm, approx.
- Weight: 174 g approx.

Supplied with a nylon case for transport and storage.  
According with standards EN61010-1, EN61010-2-032, EN61326, IEC 62321.